



# Installatie handleiding Tiptel toestellen

V. 05-12-2012



Hieronder vindt u uitleg en afbeeldingen met betrekking tot de installatie van een Tiptel toestel. De onderstaande screenshot zal in bijna alle gevallen gelijk zijn maar kan soms afwijken.

## Een account instellen

Voert u de gegevens in welke hieronder zijn gemarkeerd

Label = Uw naam

Display Name = Deze naam ziet de gene wie u belt (intern)

Register Name = Voer hier uw ontvangen gebruikersnaam in

Register Name = Voer hier uw ontvangen gebruikersnaam in

Password = Hier voert u uw ontvangen wachtwoord in

Sip Server = Voer hier: **voipmobiel.vdbcomputers.nl** in

A screenshot of a web-based configuration interface for a SIP account. The interface is titled 'Account' and shows 'Account 1' selected in a dropdown menu. Below this, there is a 'Basic >>' section. The configuration is presented in a table-like format with two columns: 'Accounts Status' and 'Registered'. The 'Accounts Status' column contains 'Account Active'. The 'Registered' column contains 'On' (selected) and 'Off'. Below these are several input fields, each with a question mark icon to its right. The fields are: 'Label' (Jeroen van den Booga), 'Display Name' (Jeroen van den Booga), 'Register Name' (1000), 'User Name' (1000), 'Password' (masked with dots), 'SIP Server' (voipmobiel.vdbcomput), 'Port' (5060), 'Enable Outbound Proxy Server' (Disabled), and 'Outbound Proxy Server' (empty) with 'Port' (5060).

## De juiste codec instellen

Om de geluidskwaliteit van uw gesprekken te garanderen, dient u de onderstaande afbeelding exact over te nemen.

The screenshot shows a web-based configuration interface for an account. At the top, there is a dropdown menu for 'Account' set to 'Account 1'. Below this are three main sections: 'Basic >>', 'Codecs >>' (with a help icon), and 'Advanced >>'. The 'Codecs >>' section contains two lists of codecs. The 'Disable codecs' list on the left includes G723\_63, G726-24, G726-32, and G726-40. The 'Enable codecs' list on the right includes PCMA, PCMU, G722, G729, G723\_53, and G726-16. Between the lists are '>>' and '<<' buttons. To the right of the 'Enable codecs' list are up and down arrow buttons. At the bottom of the interface are 'Confirm' and 'Cancel' buttons.

Na deze handelingen kunt u gebruik maken van uw tiptel voip toestel. Wij raden aan geen overige wijzigingen aan te brengen. Deze zoude de kwaliteit van het gesprek kunnen beïnvloeden. Uiteraard kunt u de instellingen met betrekking tot bel tonen en telefoonboek wel aanpassen.